

DEVELOPMENT : FINAL
 # RIR610B
 DESIGN : FINAL
 TECHNIQUE : FINAL
 Rev. : 038
 S/W VERSION : UNDEFINED
 MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W
 4/09/17 13:31:08 1

PL3361.TXT
 P A R T S L I S T

=====

()

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q'TY	UT	G	KON	OPT	REFERENCE-NO
		ECO-DATE	ECO-NO.						
1	2	533-61C-A	COVER ASS'Y	1.000	EA	A			
		3/06/11							
	3	420-107-6	SPEAKER 8 OHM 3.0W 77MM P-302RL	1.000	EA	B	SUB		
		3/06/11							
	3	623-344	(+) TAPPING SCREW(BH) 3X8-2S BLK	3.000	EA	B	SUB		SPK MTG
		3/08/20							
	3	633-082	(+) TAP TITE SCREW BH3X6 BLK	4.000	EA	B	SUB		UPPER/BOTTOM COVER MTG
		3/08/20							
	3	633-152	(+) TAP TITE SCREW BH3X4-3S BLK	2.000	EA	B	SUB		UP/BOTT REAR COVER MTG
		3/08/20							
	3	719-072-E	COVER UPPER SPC+VINYL SHEET TO. 75 BLK	1.000	EA	B	SUB		
		4/07/05 C CT04-0592							
	3	719-073-A	COVER BOTTOM SPC+VIN. SHT. TO. 75 BLK(ALAN48+)	1.000	EA	B	SUB		
		3/08/20							
	3	730-015-A	HOLDER(SPK) EGI T1 USCOATING	3.000	EA	B	SUB		SPK MTG
		3/08/20							
	3	891-590	CUSHION 25X25XT5 RUBB. SPO. BLK STIC.	1.000	EA	B	SUB		
		3/08/20							
	3	900-708	FELT &77XT0.3 FELT	1.000	EA	B	SUB		SPK HOLE
		3/08/20							
	3	901-794-A	FELT 8X45XT0.3 FELT STIC. ALAN48PLUS	4.000	EA	B	SUB		FRONT: 2 BACK: 2
		3/08/20							
2	2	533-61E-SC	ESCUTCHEON ASS'Y	1.000	EA	A			
		3/08/20							
	3	611-095	(+) MACHINE SCREW(FH) 2.6X5 ZN-PLAT	4.000	EA	B	SUB		ESC + MAIN BODY MTG
		3/08/20							
	3	801-317	E. S. C ABS 94HB BLK L380-9001	1.000	EA	B	SUB		
		3/08/20							
	3	814-286-C	LENS ACRYL	1.000	EA	B	SUB		
		4/07/24 C CT04-0659							

PL3361. TXT

3	826-404	KNOB SQL	ABS 94HB BLK		2.000	EA	B	SUB	SQL: 1 RF: 1
	3/08/20								
3	826-406	KNOB CH	ABS 94HB BLK		1.000	EA	B	SUB	
	3/08/20								
3	826-407	KNOB VOL	ABS 94HB BLK		2.000	EA	B	SUB	VOL: 1 MIC: 1
	3/08/20								
3	881-613	SPRING(VOL. SW MTG)	SK5 TO. 25		2.000	EA	B	SUB	VOL: 1 MIC: 1
	3/08/20								
3	895-572-D	KONB FUNCTION	SILICONE RUBBER		1.000	EA	B	SUB	
	4/01/26 A	CT04-0073							
3	906-867	DOUBLE TAPE(LENS)	3M-Y9448HK TO. 16		1.000	EA	B	SUB	
	3/08/20								
3	2	533-61E-SP	ESP & DC MODULE ASSY		1.000	EA	A		
	3/08/18 A	CT03-KATHI							
3	002-102-9Z	FILM RESISTOR	1K 1/ 8W 5% ST		1.000	EA	B	MAN	R2A
	4/07/21 C	CT04-0624							
3	002-271-8Z	FILM RESISTOR	270 1/ 8W 5% ST		1.000	EA	B	MAN	R4A
	4/05/14 C	AT04-KATHI							
3	002-681-5Z	FILM RESISTOR	680 1/ 8W 5% ST		2.000	EA	B	MAN	R3A. 8A
	4/05/14 C	AT04-KATHI							
3	030-181-9Z	FILM RESISTOR	180 1/ 2W 5% ST MINI		1.000	EA	B	MAN	R1A
	4/05/14 C	AT04-KATHI							
3	030-229-0Z	FILM RESISTOR	2.2 1/ 2W 5% ST MINI		2.000	EA	B	MAN	R7A. 9A
	4/05/14 C	AT04-KATHI							
3	036-338-5	CEMENT RESISTOR	0.33 5W 5% ST		1.000	EA	B	MAN	R5A
	4/05/14 C	AT04-KATHI							
3	05B-100-2Z	CHIP RESISTOR	10 1/16W 5% T 1608		1.000	EA	B	SMD	R35
	3/08/18 A	CT03-KATHI							
3	05B-101-3Z	CHIP RESISTOR	100 1/16W 5% T 1608		1.000	EA	B	SMD	R10
	3/08/18 A	CT03-KATHI							
3	05B-102-4Z	CHIP RESISTOR	1K 1/16W 5% T 1608		4.000	EA	B	SMD	R11. 13. 37. 40
	3/08/18 A	CT03-KATHI							
3	05B-103-5Z	CHIP RESISTOR	10K 1/16W 5% T 1608		1.000	EA	B	SMD	R2
	3/08/18 A	CT03-KATHI							
3	05B-104-6Z	CHIP RESISTOR	100K 1/16W 5% T 1608		7.000	EA	B	SMD	R4. 7. 15. 16. 18. 21. 39
	3/08/18 A	CT03-KATHI							
3	05B-222-9Z	CHIP RESISTOR	2.2K 1/16W 5% T 1608		4.000	EA	B	SMD	R6. 9. 14. RV1
	3/08/18 A	CT03-KATHI							
3	05B-223-0Z	CHIP RESISTOR	22K 1/16W 5% T 1608		8.000	EA	B	SMD	R1. 3. 5. 24. 27. 30. 33. 34
	3/08/18 A	CT03-KATHI							
3	05B-224-1Z	CHIP RESISTOR	220K 1/16W 5% T 1608		1.000	EA	B	SMD	R38
	3/08/18 A	CT03-KATHI							
3	05B-332-5Z	CHIP RESISTOR	3.3K 1/16W 5% T 1608		1.000	EA	B	SMD	R51
	3/08/18 A	CT03-KATHI							

		PL3361. TXT					
3	05B-472-8Z	CHIP RESISTOR	4.7K	1/16W 5% T 1608	1.000	EA B SMD	R17
3/08/18	A	CTO3-KATHI					
3	05B-473-9Z	CHIP RESISTOR	47K	1/16W 5% T 1608	8.000	EA B SMD	R8. 20. 25. 26. 28. 29. 31. 32
3/08/18	A	CTO3-KATHI					
3	071-503-5Z	RESISTOR SEMI FIXED	50K	PRM-065	2.000	EA B MAN	RV2. 3
4/08/17	C	AT04-PAT					
3	101-124-5	ELECT CAPACITOR	100UF	25V 20% 6.3X11	1.000	EA B MAN	C6A
4/05/14	C	AT04-KATHI					
3	102-278-6Y	ELECT CAPACITOR	2200UF	25V 20% 13X25	1.000	EA B MAN	C5A
4/07/21	C	CT04-0624					
3	102-300-2	ELECT CAPACITOR	22UF	16V 20% 4X7	1.000	EA B MAN	C2A
4/05/14	C	AT04-KATHI					
3	130-A73-6Y	CHIP CERAMIC	0.01UF	GRM39 X7R103K 25V	4.000	EA B SMD	C3. 14. 15. 16
3/08/18	A	CTO3-KATHI					
3	130-A74-7Y	CHIP CERAMIC	0.1UF	GRM39 Y5V104Z 25V PT	1.000	EA B SMD	C2
3/08/18	A	CTO3-KATHI					
3	130-A75-8Y	CHIP CERAMIC	0.001UF	GRM39 X7R102K 50V PT	1.000	EA B SMD	C21
3/08/18	A	CTO3-KATHI					
3	130-B06-6Y	CHIP CERAMIC	0.15UF	GRM39Y5V 154Z 16V TT	1.000	EA B SMD	C4
3/08/18	A	CTO3-KATHI					
3	130-101-8	DISK CERAMIC	0.001UF	F 102Z 50V	3.000	EA B MAN	C1A. 3A. 4A
4/05/14	C	AT04-KATHI					
3	130-249-9	CHIP CERAMIC	0.0022UF	GRM39 X7R222J 50V PT	2.000	EA B SMD	C9. 10
3/08/18	A	CTO3-KATHI					
3	130-261-9Y	CHIP CERAMIC	0.022UF	GRM39 X7R223K 50V PT	2.000	EA B SMD	C6. 17
3/08/18	A	CTO3-KATHI					
3	130-432-7Y	CHIP CERAMIC	0.0047UF	GRM39 X7R472K 50V PT	3.000	EA B SMD	C11. 12. 13
3/08/18	A	CTO3-KATHI					
3	131-093-9Y	CHIP CERAMIC	100PF	GRM39 COG101J 50V PT	1.000	EA B SMD	C5
3/08/18	A	CTO3-KATHI					
3	134-775-7Y	CHIP CERAMIC	0.047UF	GRM39 X7R473K 16V PT	1.000	EA B SMD	C7
3/08/18	A	CTO3-KATHI					
3	141-036-1Z	CHIP TANTALUM	1UF	293D105X0016A2T16V	2.000	EA B SMD	C8. 20
3/08/18	A	CTO3-KATHI					
3	141-072-3Y	CHIP TANTALUM	10UF	TSM1A106ASSR 10V	3.000	EA B SMD	C1. 18. 19
3/08/18	A	CTO3-KATHI					
3	200-332-2	TRANSISTOR	KTD1413		2.000	EA B SUB	Q3A. 5A
4/01/06	C	AT04-KATHI					
3	202-023-3	TRANSISTOR	KTC3198(GR)		1.000	EA B MAN	Q2A
4/05/14	C	AT04-KATHI					
3	202-036-5	TRANSISTOR	KTA1266(GR)		1.000	EA B MAN	Q4A
4/05/14	C	AT04-KATHI					
3	202-183-4	FET	KTK211GR		1.000	EA B SMD	Q1
3/08/18	A	CTO3-KATHI					

		PL3361. TXT			
3	222-018-5A I. C	KIA324F-EL		3.000 EA B SMD	IC1. 2. 3
3/08/18	A CT03-KATHI				
3	241-062-5 DIODE ZENER	UZ-15BM		2.000 EA B MAN	D2A. 3A
4/05/14	C AT04-KATHI				
3	243-049-4 DIODE SI CHIP	KDS226		2.000 EA B SMD	D1. 2
3/08/18	A CT03-KATHI				
3	245-015-3X DIODE RECTIFIER	1N4004		1.000 EA B MAN	D1A
4/07/21	A CT04-0624				
3	411-385-B P. C. B ESP&DC TO DO	M121. 4X35. 5 X1. 6 FR4 1/1		1.000 EA B SMD	
4/05/11	C CT04-0429				
3	420-692-5 RELAY	BS-114S-10A-24VDC		1.000 EA B MAN	RLA1
4/05/14	C AT04-KATHI				
3	505-023 HOUSING ASS' Y(6P)	SHD-8901		1.000 EA B MAN	J1
4/05/14	C AT04-KATHI				
4	2	533-61M-A MIC ASS' Y		1.000 EA A	
3/06/11					
3	002-223-5Z FILM RESISTOR	22K 1/ 8W 5% ST		1.000 EA B SUB	R901
3/06/11					
3	130-101-8Y DISK CERAMIC	0.001UF F 102Z 50V		1.000 EA B SUB	C950
3/06/11					
3	411-941 P. C. B MIC	32.17X38X1.6T XPC 94HB		1.000 EA B SUB	
3/06/11					
3	420-205-9W MIC CONDENSER	YCM9765-W-005		1.000 EA B SUB	C - MIC
3/06/11					

DEVELOPMENT : FINAL
RIR610B
DESIGN : FINAL
TECHNIQUE : FINAL
Rev. : 038

P A R T S L I S T

=====

S/W VERSION : UNDEFINED
MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W
4/09/17 13:31:08 2

()

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q' TY	UT G KON OPT	REFERENCE-NO
		ECO-DATE	ECO-NO.			
3		420-362-7Z	CORD DURL	1.000	EA B SUB	
4/05/14	C	CT04-0449				
3		421-069-8	MIC CONNECTOR	1.000	EA B SUB	J106
3/06/11						

		PL3361. TXT					
3	432-064-8Y	PUSH SWITCH	SKPS-2251N	1.000	EA	B SUB	SW102
	3/06/11						
3	436-059-7Z	SW TACT	TM115AP	2.000	EA	B SUB	SW103.104
	3/06/11						
3	600-718	(-) SECURING SCREW	ABS M6X8(P: 1) BLK	2.000	EA	B SUB	ACCESSORY
	3/08/20						
3	623-627	(+) TAPPING SCREW(BH) 3X8-2S NI-PLAT		2.000	EA	B SUB	ACC. FOR MIC BRKT
	3/08/20						
3	625-007	(+) TAPPING SCREW(TH) 5X12-1S ZN-PLAT		3.000	EA	B SUB	ACC. FOR SET BRKT
	3/08/20						
3	660-138	WASHER	RUBB. &7X&25XT1.5 BLK	2.000	EA	B SUB	ACCESSORY
	3/08/20						
3	664-320	WASHER(LOCK"B"TYPE) M3 NI-PLAT		2.000	EA	B SUB	ACC. FOR MIC BRKT
	3/08/20						
3	664-518	WASHER(LOCK"B"TYPE) M5 ZN-PLAT		3.000	EA	B SUB	ACC. FOR SET BRKT
	3/08/20						
3	693-026	(+) PLUS SCREW (P. H) 3X8 ZN-PLAT		3.000	EA	B SUB	PCB: 2 HOLDER: 1
	3/08/20						
3	693-197	(+) PLUS SCREW (P. H) 3X12(S: 10) BLK-PLAT		2.000	EA	B SUB	COVER MTG
	3/08/20						
3	718-935-BA	COVER UPPER	ABS94 L380-9001 BLK(ALAN48+)	1.000	EA	B SUB	
	3/08/20						
3	718-936	COVER BOTTOM(MI C)	ABS94HB BLK	1.000	EA	B SUB	
	3/08/20						
3	720-095	BRACKET(MI C)	SKD-5 CR-PLAT	1.000	EA	B SUB	
	3/08/20						
3	723-655-A	BRACKET	SPC T2 BLK-SPRAY	1.000	EA	B SUB	
	3/08/20						
3	731-940-A	HOLDER(MI C)	PC BLK	1.000	EA	B SUB	
	3/08/20						
3	740-547	LEVER	ABS94HB BLK	1.000	EA	B SUB	
	3/08/20						
3	825-030-A	KNOB CODE	ABS 94HB BLK	2.000	EA	B SUB	
	3/08/20						
3	870-036	WIRE CLAMP (CORD)	NYLON	1.000	EA	B SUB	
	3/08/20						
3	894-526	CUSHION	&12XT5 RUBB. SPO. BLK STIC.	1.000	EA	B SUB	
	3/08/20						
3	895-187	RUBBER SPONG	&9X&16XT10 EVA	1.000	EA	B SUB	
	3/08/20						
3	91B-657	BOX MI C	SW1S 222(W) X68(D) X58(H)	1.000	EA	B FIN	
	3/08/20						
3	921-010-EA	POLYBAG(PRINT)	P. E 100X100XT0.05	2.000	EA	B FIN	ACCESSORY
	3/08/20						

PL3361. TXT

	3	921-020-EA	POLYBAG (PRINT)	P. E 100X200XT0.05	1.000 EA B FIN	MIC
	3/08/20					
5	2	533-61M-BA	MAIN BODY ASS'Y		1.000 EA A	
	3/06/11					
	3	202-066-2	TRANSISTOR	KT B1367	1.000 EA B SUB	Q258
	3/06/11					
	3	204-010-1	TRANSISTOR	2SC2078(E)	1.000 EA B SUB	Q307
	3/11/28	C CT03-1252				
	3	204-016-7	TRANSISTOR	2SC2314(E)	1.000 EA B SUB	Q306
	3/06/11					
	3	222-006-4	I. C	KI A7217AP	1.000 EA B SUB	IC104
	3/06/11					
	3	420-020-8X	METER E. I	H321-9028A	1.000 EA B SUB	
	3/06/11					
	3	420-705-1Z	JACK DC	TC38-078-01	2.000 EA B MAN	J101.102
	3/06/11					
	3	420-726-3X	JACK MINIATURE	FJ-2506 2.5MM	1.000 EA B MAN	J103
	3/06/11					
	3	421-046-7	CONNECTOR	CH-239(A) SW-1229	1.000 EA B SUB	J104
	3/06/11					
	3	440-005-1	MICA	(FOR T. R 2SC2314)	1.000 EA B SUB	TR C2314 MTG
	3/06/11					
	3	440-020-4	MICA	0.1T: 15X13 MICA FOR TR	1.000 EA B SUB	
	3/06/11					
	3	504-892	MOLEX PLUG ASS'Y		1.000 EA S SUB	
	3/06/11					
	3	613-305	(+) MACHINE SCREW(BH) 3X8 ZN-PLAT		3.000 EA B SUB	TR MTG: 3
	4/01/26	C CT04-0073				
	3	613-332	(+) MACHINE SCREW(BH) 3X10 ZN-PLAT		3.000 EA B SUB	TR MTG: 2 IC MTG: 1
	3/08/20					
	3	621-420	(+) TAPPING SCREW(PH) 2.6X8-2S ZN-PLAT		2.000 EA B SUB	SUB PCB MTG: 2
	3/08/20					
	3	623-265	(+) TAPPING SCREW(BH) 3X6-2S ZN-PLAT		8.000 EA B SUB	MAIN PCB MTG: 6 , HEAT
SINK MTG	4/01/26	C CT04-0073				
	3	651-024	NUT	SS41 M3-1S ZN-PLAT	6.000 EA B SUB	: 2 TR MTG: 5, IC MTG: 1
	4/01/26	C CT04-0073				
	3	660-590	WASHER FIBER	7&X3. 2& 1T RED	2.000 EA B SUB	TR MTG: 2
	3/08/20					
	3	662-305	WASHER (SPRING)	M3 ZN-PLAT	4.000 EA B SUB	TR MTG: 3 IC MTG: 1
	4/01/19	C CT04-KATHI				
	3	702-426-D	BODY MAIN	EGI T1.0 US COATING	1.000 EA B SUB	
	4/01/26	A CT04-0073				
	3	732-560	HOLDER(ANT MTG)	SPT E TO. 3	1.000 EA B SUB	

PL3361. TXT

	3/08/20										
	3	750-766	CORD STOPPER	PP					1.000	EA	B SUB
		3/08/20									
	3	760-704	HEAT SINK(IC MTG)	ALP 30X18XT2					1.000	EA	B SUB
		3/08/20									
	3	761-801	HEAT SINK	AL PLATE T2.0					1.000	EA	B SUB
		4/01/26 A CT04-0073									
	3	853-105	BUSHING	NYLON66+GLASS					1.000	EA	B SUB TR MTG
		3/08/20									
6	2	533-61M-PA	MAIN PCB AUTO ASS' Y						1.000	EA	A
		3/06/11									
	3	002-100-7Z	FILM RESISTOR	10 1/ 8W 5% ST					1.000	EA	B AUT R519
		4/07/21 A CT04-0624									
	3	002-101-8Z	FILM RESISTOR	100 1/ 8W 5% ST					5.000	EA	B AUT R113. 206. 254. 312. 468
		3/10/10 C CT03-1070									
	3	002-102-9Z	FILM RESISTOR	1K 1/ 8W 5% ST					11.000	EA	B AUT
R106.	125.	253.	268.	406.	418.	460.	4/07/21 C CT04-0624				
											512. 517. 521. 526
	3	002-103-0Z	FILM RESISTOR	10K 1/ 8W 5% ST					17.000	EA	B AUT
R22.	108.	165.	171.	267.	401.	402.	4/07/21 C CT04-0624				
											403. 405. 411. 414. 415. 462. 465. +
											466. 513. 311
	3	002-104-1Z	FILM RESISTOR	100K 1/ 8W 5% ST					10.000	EA	B AUT
R166.	168.	169.	172.	173.	180.	209.	3/06/25 C CT03-KATHI				
											264. 516. 520
	3	002-106-3Z	FILM RESISTOR	10M 1/ 8W 5% ST					1.000	EA	B AUT R176
		3/06/11									
	3	002-109-6Z	FILM RESISTOR	1 1/ 8W 5% ST					1.000	EA	B AUT R313
		3/10/10 C CT03-1070									
	3	002-122-7Z	FILM RESISTOR	1.2K 1/ 8W 5% ST					1.000	EA	B AUT R151
		3/10/10 C CT03-1070									
	3	002-123-8Z	FILM RESISTOR	12K 1/ 8W 5% ST					1.000	EA	B AUT R463
		3/08/15 C CT03-KATHI									
	3	002-151-3Z	FILM RESISTOR	150 1/ 8W 5% ST					2.000	EA	B AUT R257. 316
		3/06/11									
	3	002-152-4Z	FILM RESISTOR	1.5K 1/ 8W 5% ST					3.000	EA	B AUT R256. 506. 518
		3/12/22 C CT03-1345									
	3	002-153-5Z	RESISTOR FILM	15K 1/8W 5% ST					3.000	EA	B AUT R215. 412. 455
		3/06/25 C CT03-KATHI									
	3	002-154-6Z	FILM RESISTOR	150K 1/ 8W 5% ST					1.000	EA	B AUT R301
		3/06/11									
	3	002-155-7Z	FILM RESISTOR	1.5M 1/ 8W 5% ST					1.000	EA	B AUT R451
		3/06/11									

3 002-183-2Z FILM RESISTOR 18K 1/ 8W 5% ST PL3361. TXT 1.000 EA B AUT R457
 3/10/10 C CT03-1070

DEVELOPMENT : FINAL P A R T S L I S T

RI R610B

DESIGN : FINAL

TECHNIQUE : FINAL

Rev. : 038

S/W VERSION : UNDEFINED

MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W ()

4/09/17 13:31:08 3

SEQ LEVEL PART-NO. NAME & DESCRIPTION Q'TY UT G KON OPT REFERENCE-NO
 ECO-DATE ECO-NO.

3	002-202-6Z	FILM RESISTOR	2K	1/ 8W 5% ST	1.000	EA B AUT	R453
	4/05/17 C	CT04-0457					
3	002-221-3Z	FILM RESISTOR	220	1/ 8W 5% ST	3.000	EA B AUT	R111. 302. 417
	3/10/10 C	CT03-1070					
3	002-222-4Z	FILM RESISTOR	2.2K	1/ 8W 5% ST	12.000	EA B AUT	
R56. 158. 205. 213. 216. 252. 258.	3/10/10 C	CT03-1070					261. 265. 416. 450. 471
3	002-223-5Z	FILM RESISTOR	22K	1/ 8W 5% ST	3.000	EA B AUT	R160. 170. 203
	3/06/25 C	CT03-KATHI					
3	002-229-1Z	FILM RESISTOR	2.2	1/ 8W 5% ST	1.000	EA B AUT	R317
	3/12/22 C	CT03-1345					
3	002-272-9Z	FILM RESISTOR	2.7K	1/ 8W 5% ST	1.000	EA B AUT	R504
	3/08/15 A	CT03-KATHI					
3	002-273-0Z	FILM RESISTOR	27K	1/ 8W 5% ST	1.000	EA B AUT	R218
	3/10/10 C	CT03-1070					
3	002-331-9Z	FILM RESISTOR	330	1/ 8W 5% ST	1.000	EA B AUT	R255
	3/06/11						
3	002-332-0Z	FILM RESISTOR	3.3K	1/ 8W 5% ST	1.000	EA B AUT	R266
	3/08/15 A	CT03-KATHI					
3	002-333-1Z	FILM RESISTOR	33K	1/ 8W 5% ST	3.000	EA B AUT	R456. 469. 508
	4/02/09 C	CT04-0124					
3	002-335-3Z	FILM RESISTOR	3.3M	1/ 8W 5% ST	1.000	EA B AUT	R177
	3/06/11						
3	002-392-4Z	FILM RESISTOR	3.9K	1/ 8W 5% ST	1.000	EA B AUT	R161
	4/07/21 A	CT04-0624					
3	002-393-5Z	FILM RESISTOR	39K	1/ 8W 5% ST	1.000	EA B AUT	R157

PL3361. TXT

3/10/10 A CT03-1070							
3 002-470-1Z FILM RESISTOR	47	1/ 8W 5% ST		2.000 EA B AUT		R117. 263	
3/06/11							
3 002-471-2Z FILM RESISTOR	470	1/ 8W 5% ST		5.000 EA B AUT		R115. 116. 152. 217. 467	
4/07/21 C CT04-0624							
3 002-472-3Z FILM RESISTOR	4.7K	1/ 8W 5% ST		11.000 EA B AUT			
R181. 201. 208. 211. 214. 307. 308.	3/08/23 C	CT03- KATHI					
3 002-473-4Z FILM RESISTOR	47K	1/ 8W 5% ST		15.000 EA B AUT		413. 432. 434. 507	
R103. 122. 129. 156. 159. 163. 178.	4/02/09 C	CT04-0124					
219. 262. 306. 452. 458. 461. 470. +							
3 002-474-5Z FILM RESISTOR	470K	1/ 8W 5% ST		1.000 EA B AUT		514	
3/06/25 C CT03- KATHI						R202	
3 002-561-0Z FILM RESISTOR	560	1/ 8W 5% ST		1.000 EA B AUT		R55	
3/06/11							
3 002-562-1Z FILM RESISTOR	5.6K	1/ 8W 5% ST		1.000 EA B AUT		R464	
3/10/10 A CT03-1070							
3 002-563-2Z FILM RESISTOR	56K	1/ 8W 5% ST		4.000 EA B AUT		R162. 175. 511. 515	
3/06/11							
3 002-681-5Z FILM RESISTOR	680	1/ 8W 5% ST		1.000 EA B AUT		R421	
3/10/10 C CT03-1070							
3 002-683-7Z FILM RESISTOR	68K	1/ 8W 5% ST		1.000 EA B AUT		R164	
3/08/15 C CT03- KATHI							
3 002-752-2Z FILM RESISTOR	7.5K	1/ 8W 5% ST		2.000 EA B AUT		R54. 502	
3/08/15 A CT03- KATHI							
3 030-100-6Z FILM RESISTOR	10	1/ 2W 5% ST MINI		1.000 EA B AUT		R167	
3/10/10 C CT03-1070							
3 030-100-6Z FILM RESISTOR	10	1/ 2W 5% ST MINI		1.000 EA B MAN		R259	
3/06/11							
3 030-472-2Z FILM RESISTOR	4.7K	1/ 2W 5% ST MINI		1.000 EA B MAN		R319	
3/06/11							
3 030-479-3Z FILM RESISTOR	4.7	1/ 2W 5% ST MINI		1.000 EA B MAN		R318	
3/08/15 A CT03- KATHI							
3 098-501-3 THERMISTOR DISK	500	KC5C150L		1.000 EA B MAN		TH401	
3/10/10 A CT03-1070							
3 100-101-9Y ELECT CAPACITOR	0.1UF	50V 20% 5X11		1.000 EA B AUT		C468	
3/06/11							
3 101-006-2Y ELECT CAPACITOR	1UF	50V 20% 5X11	2.5PT	3.000 EA B AUT		C165. 457. 458	
3/12/22 C CT03-1345							
3 101-012-7Z ELECT CAPACITOR	10UF	16V 20% 5X11		6.000 EA B AUT			
C161. 173. 176. 255. 411. 518	3/06/11						
3 101-012-7Z ELECT CAPACITOR	10UF	16V 20% 5X11		1.000 EA B MAN		C232	

PL3361. TXT

3/10/10 C CT03-1070	3	101-117-9	ELECT CAPACITOR	1000UF	16V 20% 10X16		1.000	EA	B	AUT	C259
3/06/11	3	101-124-5	ELECT CAPACITOR	100UF	25V 20% 6.3X11		2.000	EA	B	AUT	C252. 406
3/06/11	3	101-124-5	ELECT CAPACITOR	100UF	25V 20% 6.3X11		2.000	EA	B	MAN	C228. 466
3/10/10 C CT03-1070	3	102-207-2X	ELECT CAPACITOR	2.2UF	50V 20% 5X11	2.5PT	1.000	EA	B	MAN	C257
3/10/10 A CT03-1070	3	102-210-4Z	ELECT CAPACITOR	22UF	16V 20% 5X11		1.000	EA	B	AUT	C129
3/06/11	3	102-301-3	ELECT CAPACITOR	220UF	35V 20% 8X12		1.000	EA	B	AUT	C222
4/02/09 C CT04-0124	3	103-313-9Y	ELECT CAPACITOR	33UF	16V 20% 5X11		1.000	EA	B	AUT	C216
3/06/11	3	104-707-7Y	ELECT CAPACITOR	4.7UF	50V 20% 5X11	2.5PT	1.000	EA	B	AUT	C215
4/02/09 C CT04-0124	3	104-771-4X	ELECT CAPACITOR	47UF	16V 20% 5X11		2.000	EA	B	AUT	C213. 408
3/10/10 C CT03-1070	3	104-813-9X	ELECT CAPACITOR	470UF	16V 20% 8X12		3.000	EA	B	AUT	C211. 221. 402
4/02/09 C CT04-0124	3	130-164-6Z	AXIAL CERAMIC	0.1UF	SA105E104ZAA	50V	17.000	EA	B	MAN	
C54. 156. 157. 158. 159. 166. 168.		3/08/15 C CT03-KATHI									
170. 175. 177. 178. 212. 218. 451. +											456. 465. 467
	3	130-187-7	AXIAL CERAMIC	0.001UF	UP050B102MK	50V	5.000	EA	B	AUT	C105. 201. 202. 207. 455
	3/06/11										
	3	130-188-8Z	AXIAL CERAMIC	0.01UF	EP050Y103MN	16V	8.000	EA	B	AUT	
C104. 108. 126. 127. 151. 234. 407.		4/02/13 C CT04-0147									
	3	130-203-9	AXIAL CERAMIC	0.0022UF	EP050X222MN	16V	1.000	EA	B	AUT	452
	3/06/11										C205
	3	130-227-9	AXIAL CERAMIC	0.022UF	RH050F	223Z 50V	5.000	EA	B	AUT	C167. 171. 206. 506. 520
	4/02/09 C CT04-0124										
	3	130-418-5	AXIAL CERAMIC	0.0047UF	EP050X472MN	16V	1.000	EA	B	AUT	C227
	3/06/11										
	3	130-427-3	AXIAL CERAMIC	0.047UF	UP050F473ZB	50V	1.000	EA	B	AUT	C203
	3/06/11										
	3	130-613-4	AXIAL CERAMIC	0.0068UF	EP050X682K	16V	1.000	EA	B	AUT	C172
	3/06/11										
	3	138-002-2	DISK CERAMIC	8PF	NP0080D	50V	1.000	EA	B	MAN	C24
	4/07/21 A CT04-0624										
	3	140-401-2	DIP TANTALUM	0.47UF	ECSF1VE474M	16V	1.000	EA	B	MAN	C500

PL3361. TXT

4/08/26 C CT04-0773	3	141-004-2	DIP TANTALUM	1UF	TAM1E010AMCB	25V	1.000	EA	B	SUB	C503
4/08/26 C CT04-0773	3	196-802-6Z	MYLAR CAPACITOR	0.0068UF		682J 50V	1.000	EA	B	MAN	C461
3/06/11	3	202-023-3X	TRANSISTOR		ST2SC3198G(ECB-M)	1.000	EA	B	AUT	Q402
3/10/10 A CT03-1070	3	241-004-3X	DIODE ZENER		1N5237BST		1.000	EA	B	MAN	DZ1
3/10/10 A CT03-1070	3	243-019-7	DIODE		1N4148(R. L)		24.000	EA	B	AUT	
D101. 102. 121. 151. 152. 153. 4/07/21 C CT04-0624											
154. 155. 156. 201. 202. 203. 205. +											
252. 301. 302. 415. 416. 432. 451.											
											452. 453. 506. 56
3/06/11	3	311-972-9Z	COIL SPRING		R4251-CS57-	854392	1.000	EA	B	MAN	L312
4/08/25 C CT04-0742	3	4A1-186-C	P. C. B ASS'Y	187	X160	X1.6 XPC-94HB	1/0	1.000	EA	B	AUT
4/08/24 A CS-CSKANG	4	401-165-C	P. C. B MAIN	153.	5X145.	4X1.6 XPC-94HB	1/0	1.000	EA	B	MAN

 DEVELOPMENT : FINAL
 # RIR610B
 DESIGN : FINAL
 TECHNIQUE : FINAL
 Rev. : 038
 S/W VERSION : UNDEFINED
 MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W
 4/09/17 13:31:08 4

P A R T S L I S T

=====

()

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q'TY	UT	G	KON	OPT	REFERENCE-NO
		ECO-DATE	ECO-NO.						
		4	411-816-C P. C. B VOLUME	32.5	X23.2	X1.6	XPC-94HB	1/0	1.000 EA B MAN
		4/08/24 A	CS-CSKANG						
7	2	533-61M-PM	MAIN PCB MANUAL ASSY						1.000 EA A
		3/06/11							
		3	019-100-5 METAL OXIDE RESISTOR10				2W 5% ST		2.000 EA B MAN
		3/12/22 C	CT03-1345						R803. 809

				PL3361. TXT						
3	019-479-8Z	METAL OXIDE RESISTOR	4.7	2W 5% ST		1.000	EA	B	MAN	R207
	3/06/11									
3	030-181-9Z	FILM RESISTOR	180	1/ 2W 5% ST MINI		1.000	EA	B	MAN	R805
	3/06/11									
3	061-109-9	RESISTOR SEMI FIXED	10KB	PC805M H 8DIA		2.000	EA	B	MAN	RV101. 203
	3/06/11									
3	061-205-2	RESISTOR SEMI FIXED	2KB	PC805M H 8DIA		1.000	EA	B	MAN	RV201
	3/06/11									
3	061-507-7	RESISTOR SEMI FIXED	5KB	PC805M H 8DIA		1.000	EA	B	MAN	RV501
	3/06/11									
3	061-508-8	RESISTOR SEMI FIXED	50KB	PC805M H 8DIA		2.000	EA	B	MAN	RV103. 105
	3/06/11									
3	098-201-2	THERMISTOR DISK	200 OHM 15%	KC5B120L		3.000	EA	B	MAN	TH102. 103. 105
	3/06/25 C CT03-	KATHI								
3	098-501-3	THERMISTOR DISK	500	KC5C150L		1.000	EA	B	MAN	TH55
	3/06/11									
3	101-117-9	ELECT CAPACITOR	1000UF	16V 20% 10X16		1.000	EA	B	AUT	C261
	3/06/11									
3	102-207-2X	ELECT CAPACITOR	2.2UF	50V 20% 5X11 2.5PT		1.000	EA	B	MAN	C100
	3/06/11									
3	116-803-3Z	MYLAR CAPACITOR	0.068UF	50V 10% S		1.000	EA	B	MAN	C463
	3/10/10 C CT03-	1070								
3	130-101-8Y	DISK CERAMIC	0.001UF	F 102Z 50V		1.000	EA	B	MAN	C224
	3/06/11									
3	130-102-9R	DISK CERAMIC	0.01UF	DD312B 103K 50V 794		8.000	EA	B	AUT	
	C119. 152. 223. 272. 302. 312. 313.	3/10/10 C CT03-	1070							
										343
3	130-102-9R	DISK CERAMIC	0.01UF	DD312B 103K 50V 794		13.000	EA	B	MAN	
	C116. 120A. 271. 517. 122. 125. 251.	3/08/15 C CT03-	KATHI							
										253. 256. 258. 263. 301. 804
3	130-164-6	AXIAL CERAMIC	0.1UF	SA105E104ZAA 50V		1.000	EA	B	AUT	C163
	4/07/21 A CT04-	0624								
3	130-227-9X	DISK CERAMIC	0.022UF	Y5U223M 50V		1.000	EA	B	MAN	C502
	4/08/26 C CT04-	0773								
3	130-405-3R	DISK CERAMIC	0.047UF	SDD 360Y5V 473M 794 50		7.000	EA	B	AUT	
	C111. 231. 262. 311. 328. 345. 530	3/10/10 C CT03-	1070							
3	130-405-3R	DISK CERAMIC	0.047UF	SDD 360Y5V 473M 794 50		2.000	EA	B	MAN	C162. 233
	4/07/21 C CT04-	0624								
3	131-003-8Y	DISK CERAMIC	10PF	NP0100D 50V		2.000	EA	B	MAN	C341. 523
	4/07/21 C CT04-	0624								
3	131-015-9R	DISK CERAMIC	100PF	DD330CH 101K 50V 794		3.000	EA	B	AUT	C325. 335. 524
	3/10/10 C CT03-	1070								
3	131-015-9Y	DISK CERAMIC	100PF	NP0101K 50V		1.000	EA	B	MAN	C180
	4/07/21 C CT04-	0624								

		PL3361. TXT							
3	131-204-3X DISK CERAMI C	12PF	NPO K% 50V		2.000	EA	B	MAN	C121.405
4/07/21	C CT04-0624								
3	131-226-3R DISK CERAMI C	120PF	DD380CH	121J 794 50V	1.000	EA	B	AUT	C512
4/07/21	C CT04-0624								
3	131-502-2Y DISK CERAMI C	15PF	NPO150K 50V		2.000	EA	B	MAN	C101.306
4/07/21	C CT04-0624								
3	131-510-9R DISK CERAMI C	150PF	DD380CH	151K 794 50V	1.000	EA	B	AUT	C513
3/12/22	C CT03-1345								
3	131-804-5X DISK CERAMI C	18PF	NPO K% 50V		3.000	EA	B	MAN	C117.153.307
4/07/21	C CT04-0624								
3	131-814-4 DISK CERAMI C	180PF	NPO181K 50V		2.000	EA	B	MAN	C308.316
3/10/10	C CT03-1070								
3	132-004-4Y DISK CERAMI C	2PF	NPO020D 50V		1.000	EA	B	MAN	C342
3/06/11									
3	132-202-6X DISK CERAMI C	22PF	NPO K% 50V		3.000	EA	B	MAN	C113.403.511
3/08/15	C CT03-KATHI								
3	132-214-7 DISK CERAMI C	220PF	NPO221K 50V		2.000	EA	B	MAN	C208.352
4/07/21	A CT04-0624								
3	132-214-7X DISK CERAMI C	220PF	NPO 50V		4.000	EA	B	AUT	C322.327.337.338
4/07/21	C CT04-0624								
3	132-214-7X DISK CERAMI C	220PF	NPO 50V		3.000	EA	B	MAN	C217.331.339
3/12/22	C CT03-1345								
3	133-002-7X DISK CERAMI C	3PF	NPO K% 50V		2.000	EA	B	MAN	C149.150
3/06/25	C CT03-KATHI								
3	133-004-9X DISK CERAMI C	30PF	NPO K% 50V		1.000	EA	B	AUT	C453
3/06/11									
3	133-303-9R DISK CERAMI C	33PF	NPO330K 50V		1.000	EA	B	AUT	C525
3/06/11									
3	133-311-0X DISK CERAMI C	330PF	NPO		4.000	EA	B	AUT	C254.321.326.333
4/07/21	C CT04-0624								
3	133-311-0X DISK CERAMI C	330PF	NPO		1.000	EA	B	MAN	C332
3/06/11									
3	133-902-0Y DISK CERAMI C	39PF	NPO390K 50V		2.000	EA	B	MAN	C336.522
4/04/07	C CT04-0320								
3	133-904-2 DISK CERAMI C	390PF	SL 391K 50V		2.000	EA	B	MAN	C155.317
4/07/21	C CT04-0624								
3	134-702-1R DISK CERAMI C	470PF	DD380SL	471K 794 50V	2.000	EA	B	AUT	C344.346
3/08/15	C CT03-KATHI								
3	134-708-7R DISK CERAMI C	47PF	DD350257CH	470K 50V 794	1.000	EA	B	AUT	C123
3/06/11									
3	134-708-7X DISK CERAMI C	47PF	NPO K% 50V		1.000	EA	B	MAN	C515
3/10/10	C CT03-1070								
3	135-001-6Y DISK CERAMI C	5PF	NPO050D 50V		1.000	EA	B	MAN	C521
4/07/21	C CT04-0624								

			PL3361. TXT			
	3	135-602-9	DISK CERAMI C	560PF	SL 561K 50V	1.000 EA B MAN C507
		3/10/10 C	CT03-1070			
	3	135-605-2X	DISK CERAMI C	56PF	NPO K% 50V	1.000 EA B MAN C320
		4/07/21 C	CT04-0624			
	3	136-004-4X	DISK CERMI C	6PF	NPO K% 50V	2.000 EA B MAN C107. 514
		3/06/25 C	CT03-KATHI			
	3	136-802-8	DISK CERAMI C	680PF	B 681K 50V	1.000 EA B MAN C462
		3/10/10 A	CT03-1070			
	3	136-805-1X	DISK CERAMI C	68PF	NPO K% 50V	1.000 EA B MAN C347
		4/04/07 A	CT04-0320			
	3	172-015-6W	DIP TRIMMER	20PF	CVN620	1.000 EA B MAN CT401
		3/06/11				
	3	200-040-8R	TRANSI STOR	KRC101M AT	(TO-92)	4.000 EA B AUT Q154. 403. 451. 505
		3/08/15 C	CT03-KATHI			
	3	202-023-3	TRANSI STOR	KTC3198(GR)		1.000 EA B MAN Q252
		3/06/11				
	3	202-023-3X	TRANSI STOR	ST2SC3198G(ECB- M)		6.000 EA B AUT
Q121. 151.		207. 251. 401. 404				
			4/07/21 C	CT04-0624		
	3	202-036-5	TRANSI STOR	KTA1266(GR)		1.000 EA B MAN Q208
		3/06/11				
	3	202-036-5X	TRANSI STOR	ST2SA1266G(ECB- M)		3.000 EA B AUT Q157. 253. 257
		3/06/25 C	CT03-KATHI			
	3	202-043-1R	TRANSI STOR	KTC3192(Y) AT		1.000 EA B AUT Q305
		3/06/11				
	3	202-060-7R	TRANSI STOR	KTC3194(Y) AT		3.000 EA B AUT Q503. 504. 506
		4/08/26 C	CT04-0773			
	3	202-068-4R	TRANSI STOR	KTK161(GE) AT		3.000 EA B AUT Q104. 107. 108
		3/06/11				
	3	202-121-8R	TRANSI STOR	KRC110MAT		9.000 EA B AUT
Q106. 152. 153. 201. 202. 203. 205.			3/06/11			
	3	202-122-9R	TRANSI STOR	KRC102MAT		4.000 EA B AUT 209. 303
		4/08/26 C	CT04-0773			Q255. 256. 301. 507
	3	202-184-5R	BRT	KRC112MAT		1.000 EA B AUT Q210
		3/06/11				
	3	220-818-1	IC(AM/FM DETECTOR)	TK10930VTL		1.000 EA B SUB IC102
		3/06/11				
	3	221-312-5	I. C	MC33074P		1.000 EA B MAN IC103
		3/06/11				
	3	241-004-3X	DIODE ZENER	1N5237BST		1.000 EA B AUT DZ201
		3/06/11				
	3	241-158-9Z	DIODE ZENER	1N5234B 6. 2V1/2W		1.000 EA B AUT DZ401
		3/10/10 C	CT03-1070			
	3	241-201-7Y	DIODE ZENER	1N5235BST		1.000 EA B AUT DZ403

3/06/11

DEVELOPMENT : FINAL
RIR610B

P A R T S L I S T

DESIGN : FINAL
TECHNIQUE : FINAL
Rev. : 038

=====

S/W VERSION : UNDEFINED
MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W
4/09/17 13:31:08 5

()

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q' TY	UT	G	KON	OPT	REFERENCE-NO
	ECO-DATE	ECO-NO.							
3	3/06/11	242-001-5R	DIODE VARI CAP SVC251SPA-AC	3.000	EA	B	MAN		D503.504.505
3	3/06/11	245-008-7X	DIODE RECTIFIER 1N5404	1.000	EA	B	MAN		D211
3	3/06/11	245-015-3Z	DIODE RECTIFIER 1N4004T/R 400V 1A	1.000	EA	B	MAN		D271
3	3/06/11	260-485-5V	CRYSTAL HC49U 10.240M -30 30PM 32P FUND	1.000	EA	B	MAN		X1
3	3/06/11	262-043-9Y	CRYSTAL(HC-49U) 4.5MHZ -30 30PM 16P FUND	1.000	EA	B	MAN		X401
3	4/01/28	270-007-0W	FILTER CERAMIC CT04-0084	1.000	EA	B	MAN		CF2
3	3/06/11	271-030-5Z	FILTER CRYSTAL HC49/T (10.695M)	1.000	EA	B	MAN		CF1
3	3/06/11	300-136-3W	TRANSFORMER LE119-H019	1.000	EA	B	MAN		CH201
3	3/06/11	300-159-4Z	TRANSFORMER (MOD.) EI-24	1.000	EA	B	MAN		T201
3	3/06/11	310-172-8	COIL SPRING 6.3X0.8X6T: R 0.225UH	1.000	EA	B	MAN		L311
3	3/06/11	310-291-2Z	COIL AXIAL 6.8UH: TCEC-6R8K	1.000	EA	B	AUT		L306
3	3/06/11	310-296-7Z	COIL SPRING 6X0.8X5.5T: R	1.000	EA	B	MAN		L310
3	3/06/11	310-297-8Z	COIL SPRING 2.5X0.8X7T: R	1.000	EA	B	MAN		L304
3	3/06/11	310-347-0Z	COIL SPRING 5.2X0.7X7T: R	1.000	EA	B	MAN		L313

PL3361. TXT

	3/06/11					
	3	310-407-1	COIL SPRING	5X0. 6X13. 5T: R	1. 000 EA B MAN	L307
	3/06/11					
	3	320-301-1	COIL	455KHZ DET	1. 000 EA B MAN	L105
	3/06/11					
	3	320-314-3Z	COIL IFT	Z73D- 225	1. 000 EA B MAN	L401
	3/06/11					
	3	320-318-7Z	COIL IFT	Z73C- 359	2. 000 EA B MAN	L301. 302
	3/06/11					
	3	320-380-2Y	COIL IFT	27MHZ LKSZ73D0- X000205- 0	1. 000 EA B MAN	L102
	3/06/11					
	3	320-576-3Z	COIL IFT	10. 7MHZ MAX RX	1. 000 EA B MAN	L104
	4/07/16 C	CT04- 0618				
	3	320-577-4	COIL IFT	37MHZ TX	1. 000 EA B MAN	L303
	4/07/16 C	CT04- 0618				
	3	320-585-1Z	COIL IFT	27MHZ Z073I - 1	1. 000 EA B MAN	L101
	3/06/11					
	3	321-095-2	COIL IFT	27MHZ RX (7RC)	1. 000 EA B MAN	L103
	4/07/16 C	CT04- 0618				
	3	430-073-8	SW PULSE	YPS210125SK 25MM	1. 000 EA B MAN	SW401
	3/06/11					
	3	509-110	6. 5T SPRING COIL ASS6. 5T3. 4X. 55: M9D3. 7X6		1. 000 EA B MAN	L314
	3/08/15 A	CT03- KATHI				
	4	310-809-1	COIL SPRING	3. 4X0. 55X6. 5T: R	1. 000 EA B MAN	
	93/07/09 A	B93- 0709				
	4	321-053-2	CORE	1108- KA- 058 M9DTH3. 7X6	1. 000 EA B MAN	
	93/07/09 A	B93- 0709				
	3	771-850	SHIELD PLATE	SPTE TO. 5	1. 000 EA B MAN	
	3/08/20					
	3	772-238	SHIELD HOUSING	SPTE TO. 3	1. 000 EA B MAN	
	3/08/20					
	3	772-274-A	SHIELD PLATE	SPTE T=0. 3	1. 000 EA B SUB	
	3/08/20					
	3	772-678	SHIELD PLATE	TIN TO. 3	1. 000 EA B SUB	
	4/01/26 A	CT04- 0073				
	3	906-998	TAPE CU	16X36XT0. 05 CU- TAPE	2. 000 EA B SUB	
	4/02/26 A	CT04- 0192				
	3	999-128	TAPE	TAPE MARKING 12 MM	0. 055 RL B	SUPPORT 772- 238
	4/03/17 C	AT04- KATHI				
8	2	533-61P- A	PACKING ASS' Y		1. 000 EA A	
	3/08/20					
	3	504-629	MOLEX RECEPTACLE ASS900MM		1. 000 EA S SUB	
	3/06/11					
	3	91B- 658	BOX TRAY	SW1S 226(W) X162(D) X58(H)	1. 000 EA B FIN	

PL3361. TXT

3/08/20	3	91C-002	PAD (TRC-439)	SW1S 268X21	3.000	EA	B	FIN	
3/08/20	3	91D-235-B	BOX OUT	DW1E 415(W)X244(D)X244(H)	0.167	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	91D-326	BOX INNER	SW1S "E" 238(W)X238(D)X66(H)	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	922-030-EB	POLYBAG(PRINT)	P. E 200X300XT0.05	1.000	EA	B	FIN	MANUAL
3/08/20	3	922-535-ED	POLYBAG (PRINT)	P. E 250X350XT0.05	1.000	EA	B	FIN	SET
3/08/20	3	937-854	MANUAL OWNER' S	ALAN48XL MULTI	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	937-855	MANUAL OWNER' S	ALAN48XL MULTI	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	943-244-C	WARRANTY CARD	WOOD PAPER 350X92	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	943-714	CARD WARRANTY	ARTPAPER 210X95	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	943-757	CARD WARRANTY	WOODFREEPAPER 149X105	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	943-859	CARD IMPORTANT	WOODFREEPAPER 148X210	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	95B-100	LABEL E3	FOIL STICKER 12X8	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	95B-125	LABEL ITALIAN	ARTPAPER 57X105	1.000	EA	B	FIN	
4/07/10	A	CT04-0616							
3/08/20	3	95B-172	LABEL SERIAL	ARTPAPER 30X40	1.000	EA	B	FIN	
4/08/13	A	CT04-0724							
3/08/20	3	95B-180	LABEL MULTI	POLYESTER 70X70	1.000	EA	B	FIN	
4/04/01	A	CT04-0311							
3/08/20	3	95B-199	LABEL AUTOMATIVE	POLYESTER 12X8	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	95B-200	LABEL EU COUNTRY	ARTPAPER 50X36	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	95B-201	LABEL GIFT BOX	ARTPAPER 224X50	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	95B-202	LABEL NAME	POLYESTER 68.5X16.5	1.000	EA	B	FIN	
4/09/14	A	CT04-0844							
3/08/20	3	950-040	LABEL NEGATIVE		1.000	EA	B	FIN	
4/08/23	A	CT04-0757							
3/08/20	3	953-750	LABEL CAUTION 2A	40X28XT0.02	1.000	EA	B	FIN	
4/08/23	A	CT04-0757							
3/08/20	3	954-267-A	LABEL WIRE BATTERY	PAPER 40X12	1.000	EA	B	FIN	

PL3361. TXT

9 2	4/08/23 A CT04-0757	533-61S-PA SUB PCB AUTO ASS'Y				1.000 EA A	
	3/06/11						
3	05B-000-5Z	CHIP RESISTOR	0	1/16W 5% T 1608		1.000 EA B SMD	R91
	4/01/22 A CT04-0066						
3	05B-101-3Z	CHIP RESISTOR	100	1/16W 5% T 1608		1.000 EA B SMD	R276
	3/08/15 A CT03-KATHI						
3	05B-103-5Z	CHIP RESISTOR	10K	1/16W 5% T 1608		7.000 EA B SMD	
R12. 19. 185. 186. 187. 188. 189	3/08/15 C CT03-KATHI						
3	05B-104-6Z	CHIP RESISTOR	100K	1/16W 5% T 1608		26.000 EA B SMD	
R701. 702. 703. 704. 705. 706. 707.	3/08/15 C CT03-KATHI						
708. 709. 710. 711. 712. 713. 714. +							
715. 716. 717. 718. 719. 720. 721.							
3	05B-124-4Z	CHIP RESISTOR	120K	1/16W 5% T 1608		1.000 EA B SMD	722. 723. 903. 904. 905 R428
	3/08/15 C CT03-KATHI						
3	05B-223-0Z	CHIP RESISTOR	22K	1/16W 5% T 1608		1.000 EA B SMD	R277
	3/08/15 C CT03-KATHI						
3	05B-273-5Z	CHIP RESISTOR	27K	1/16W 5% T 1608		1.000 EA B SMD	R427
	3/08/15 C CT03-KATHI						
3	05B-472-8Z	CHIP RESISTOR	4.7K	1/16W 5% T 1608		1.000 EA B SMD	R431
	3/08/15 C CT03-KATHI						
3	05B-473-9Z	CHIP RESISTOR	47K	1/16W 5% T 1608		7.000 EA B SMD	
R271. 272. 273. 274. 275. 801. 902	3/08/15 C CT03-KATHI						

DEVELOPMENT : FINAL
RIR610B

P A R T S L I S T

DESIGN : FINAL
TECHNIQUE : FINAL

=====

Rev. : 038
S/W VERSION : UNDEFINED

MODEL CODE : 3361 ALAN48XL MULTI 27MHZ 400CH 4W
4/09/17 13:31:08 6

()

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q'TY	UT	G	KON	OPT	REFERENCE-NO
		ECO-DATE	ECO-NO.						

3		05B-474-0Z	CHIP RESISTOR	470K	1/16W	5%	T	1608	1.000 EA B SMD	R906
		3/08/15 C	CT03-KATHI							

		PL3361. TXT					
3	130-A73-6Y	CHI P CERAMI C	0. 01UF	GRM39 X7R103K 25V	3. 000 EA B SMD	C138. 806. 808	
3/08/15	C CT03-KATHI						
3	130-432-7Y	CHI P CERAMI C	0. 0047UF	GRM39 X7R472K 50V PT	2. 000 EA B SMD	C442. 443	
3/08/15	C CT03-KATHI						
3	131-093-9Y	CHI P CERAMI C	100PF	GRM39 COG101J 50V PT	3. 000 EA B SMD	C250. 251. 252	
3/08/15	C CT03-KATHI						
3	131-100-6Y	CHI P CERAMI C	0. 1UF	GRM39 X7R104K 50V PT	2. 000 EA B SMD	C22. 187	
3/08/15	C CT03-KATHI						
3	132-025-3Y	CHI P CERAMI C	20PF	GRM39 COG200J 50V PT	2. 000 EA B SMD	C901. 902	
3/08/15	C CT03-KATHI						
3	202-082-6	TRANSI STOR		KTA1504ST1(G)	1. 000 EA B SMD	Q422	
3/06/25	C CT03-KATHI						
3	202-095-8Z	TRANSI STOR		KRC104SND	1. 000 EA B SMD	Q2	
3/06/25	A CT03-KATHI						
3	202-112-0	TRANSI STOR		KTC3875S(GR)	1. 000 EA B SMD	Q421	
3/06/25	C CT03-KATHI						
3	221-460-5	I. C PLL(DUAL)		BU2630F	1. 000 EA B SMD	IC6	
3/06/25	A CT03-KATHI						
3	221-531-6	I. C CPU(OTP)		S3P8249XZZ-TWR9	1. 000 EA B SUB	IC101	
4/08/17	C AT04-PAT			(NI KE)			
3	221-872-4	I. C EEPROM		HT93LC66- 8SOP- A	1. 000 EA B SMD	IC9	
3/11/17	C CT03-1205						
3	243-051-5	DI ODE SI CHI P		KDS184S	3. 000 EA B SMD	D3. 4. 11	
3/10/10	C CT03-1070						
3	252-321-7	LCD DI SPLAY		IS07167P	1. 000 EA B SUB	LCD	
3/11/17	A CT03-1205						
3	270-065-2X	RESONATOR CERAMI C		ZTA 3. 587MG	1. 000 EA B SUB	X901	
3/08/15	A CT03-KATHI						
10 2	533-61S-PM	SUB PCB MANUAL ASS' Y			1. 000 EA A		
3/06/11							
3	100-102-0Z	CAPACITOR ELECT	0. 1UF 50V	SRA(M) : 4X7	2. 000 EA B SUB	C805. 807	
3/08/15	A CT03-KATHI						
3	251-078-3Z	LED LAMP		BL- REG202H	2. 000 EA B SUB	LED1. 2	
3/06/11							
3	251-224-8Z	PI LOT LAMP		60MA 3& 14V	3. 000 EA B MAN	LP1. 2. 3	
4/05/18	C AT04-KATHI						
3	251-279-8Z	PI LOT LAMP		40MA 3& 14V	6. 000 EA B SUB	LP4. 5. 6. 7. 8. 9	
3/06/11							
3	310-291-2Z	COIL AXIAL		6. 8UH: TCEC- 6R8K	3. 000 EA B MAN	L801. 804. 805	
3/06/11							
3	411-811-B	P. C. B LCD		149 X48 X1. 6 FR4 1/1	1. 000 EA B SMD		
4/05/19	C CT04-0463						
3	421-643-6A	CONNECTOR SOCKET		SCN- 16- 6(M1) R PCB TYPE	1. 000 EA B SUB	J105	
4/02/05	C CT04-0118						

		PL3361. TXT					
3	432-040-6	SW PUSH	SPPH221AP011	1.000	EA B MAN	SW201	
	3/06/11						
3	436-059-7Z	SW TACT	TM115AP	8.000	EA B MAN	SW1. 2. 3. 4. 5. 6. 10. A	
	4/05/20	C AT04-KATHI					
3	814-287	LENS LIGHTING	ACRYL	1.000	EA B SUB		
	3/08/20						
3	826-405	KNOB CB/PA	ABS 94HB BLK	1.000	EA B SUB		
	3/08/20						
3	895-625	LAMP CAP	3\$ YELLOW	6.000	EA B SUB		
	3/08/20						
3	906-868	BACK PLATE	54. 3X22. 8XT0. 25 PC YELLOW	1.000	EA B SUB		
	3/08/20						
11	2	533-61V-RP	V/R PCB ASS' Y	1.000	EA A		
	3/06/11						
3	101-006-2Y	ELECT CAPACITOR	1UF 50V 20% 5X11 2.5PT	1.000	EA B MAN	C471	
	3/12/22	A CT03-1345					
3	429-324-8	FLAT WIRE	11PX2. OX150	1.000	EA B MAN		
	3/06/11						
3	450-534-5Z	VR	50KA: 0952-25FP-B10K	1.000	EA B MAN	VOL/SQ	
	3/06/11						
3	450-535-6Z	VR	50KB: 0951-25FP	1.000	EA B MAN	MI C/RF GAIN	
	3/06/11						
12	2	533-61W-A	WIRE ASS' Y	1.000	EA A		
	3/06/11						
3	427-002-7	WIRE	1007 AWG 24 (1/0/51) BRN	0.070	ME B MAN	A --- A1	
	3/12/22	C CT03-1345					
						1.5: 1.5	
3	427-003-8	WIRE	1007 AWG 24(1/0.51) RED	0.200	ME B MAN	L --- L1	
	3/12/22	A CT03-1345					
						1.5: 1.5	
3	427-010-4	WIRE	1007 AWG 24(1/0.51) WHT	0.110	ME B MAN	C --- C1	
	3/12/22	C CT03-1345					
						1.5: 1.5	
3	427-025-8	WIRE	1007 AWG 24(11/0.16) YEL	0.080	ME B MAN	MP MT(+) --- MET(+)	
	3/06/11						
						0.5: 0.5	
3	427-026-9	WIRE	1007 AWG 24 (11/0.16) GRN	0.080	ME B MAN	MP MT(-) --- MET(-)	
	3/06/11						
						0.5: 0.5	
3	427-269-2	WIRE	1015 AWG 20(10/0.26) RED	0.200	ME B MAN	E --- E1	
	3/12/22	A CT03-1345					
						1.5: 1.5	
3	427-270-2	WIRE	1015 AWG 20(10/0.26) BLK	0.120	ME B MAN	F --- F1	
	3/12/22	A CT03-1345					

PL3361. TXT

13	2	533-61W-MA	WIRE MIC ASS' Y			1.000 EA A	1.5:1.5
		3/06/11					
PCB SUB	3	427-025-8	WIRE	1007 AWG 24(11/0.16)	YEL	0.060 ME B SUB	CONDENSER MIC(+) ---
		3/06/11					
PCB SUB	3	427-026-9	WIRE	1007 AWG 24 (11/0.16)	GRN	0.060 ME B SUB	0.5:0.5 CONDENSER MIC(-) ---
		3/06/11					0.5:0.5

* TOTAL RECORD = 379

•